



S11 METALIZED POLYPHENYLENE SULFIDE



Axial Lead

OVAL

Wrap & Fill

LEAD LENGTH = 1.5" MIN.

Lead Gauge	50VDC	100VDC	200VDC	400VDC
24AWG	.001 - 2.0	.001 - 1.0	.001 - .33	.001 - .10
22AWG	3.0 - 8.0	1.2 - 2.0	.39 - 1.0	.12 - .27
20AWG	10.0 - 20.0	3.0 - 20.0	1.2 - 10.0	.33 - 2.0

MFD	50 VDC				100 VDC				200 VDC				400 VDC			
	T +.05	W +.05	L +.05	PART NO.	T +.05	W +.05	L +.05	PART NO.	T +.05	W +.05	L +.05	PART NO.	T +.05	W +.05	L +.05	PART NO.
.0010	.09	.18	.40	S11A102	.09	.18	.40	S11B102	.09	.18	.40	S11C102	.09	.18	.40	S11E102
.0012	.09	.18	.40	S11A122	.09	.18	.40	S11B122	.09	.18	.40	S11C122	.09	.18	.40	S11E122
.0015	.09	.18	.40	S11A152	.09	.18	.40	S11B152	.09	.18	.40	S11C152	.09	.18	.40	S11E152
.0018	.09	.18	.40	S11A182	.09	.18	.40	S11B182	.09	.18	.40	S11C182	.09	.18	.40	S11E182
.0022	.09	.18	.40	S11A222	.09	.18	.40	S11B222	.09	.18	.40	S11C222	.09	.18	.40	S11E222
.0027	.09	.18	.40	S11A272	.09	.18	.40	S11B272	.09	.18	.40	S11C272	.09	.18	.40	S11E272
.0033	.09	.18	.40	S11A332	.09	.18	.40	S11B332	.09	.18	.40	S11C332	.09	.18	.40	S11E332
.0039	.09	.18	.40	S11A392	.09	.18	.40	S11B392	.09	.18	.40	S11C392	.10	.19	.40	S11E392
.0047	.09	.18	.40	S11A472	.09	.18	.40	S11B472	.09	.18	.40	S11C472	.11	.21	.40	S11E472
.0056	.09	.18	.40	S11A562	.09	.18	.40	S11B562	.09	.18	.40	S11C562	.09	.18	.53	S11E562
.0068	.09	.18	.40	S11A682	.09	.18	.40	S11B682	.09	.18	.40	S11C682	.09	.18	.53	S11E682
.0082	.09	.18	.40	S11A822	.09	.18	.40	S11B822	.09	.18	.40	S11C822	.09	.18	.53	S11E822
.010	.09	.18	.40	S11A103	.09	.18	.40	S11B103	.09	.18	.40	S11C103	.11	.20	.53	S11E103
.012	.09	.18	.40	S11A123	.09	.18	.40	S11B123	.09	.18	.40	S11C123	.12	.22	.53	S11E123
.015	.09	.18	.40	S11A153	.09	.18	.40	S11B153	.09	.18	.40	S11C153	.14	.24	.53	S11E153
.018	.09	.18	.40	S11A183	.09	.18	.40	S11B183	.10	.19	.40	S11C183	.16	.25	.53	S11E183
.022	.09	.18	.40	S11A223	.09	.18	.40	S11B223	.11	.20	.40	S11C223	.18	.28	.53	S11E223
.027					.09	.18	.40	S11B273	.09	.18	.53	S11C273	.21	.30	.53	S11E273
.033									.09	.18	.53	S11C333	.23	.33	.53	S11E333
.039									.10	.20	.53	S11C393	.19	.29	.68	S11E393
.047									.11	.21	.53	S11C473	.21	.31	.68	S11E473
.056									.13	.22	.53	S11C563	.24	.33	.68	S11E563
.068									.15	.24	.53	S11C683	.22	.31	.78	S11E683
.082									.16	.26	.53	S11C823	.25	.34	.78	S11E823
.10									.18	.28	.53	S11C104	.28	.37	.78	S11E104
.12									.21	.30	.53	S11C124	.31	.40	.78	S11E124
.15									.23	.33	.53	S11C154	.27	.36	.95	S11E154
.18									.21	.30	.68	S11C184	.34	.43	.95	S11E184
.22									.23	.33	.68	S11C224	.28	.44	1.17	S11E224
.27									.24	.33	.78	S11C274	.31	.48	1.17	S11E274
.33									.27	.36	.78	S11C334	.35	.52	1.17	S11E334
.39									.30	.40	.78	S11C394	.39	.56	1.17	S11E394
.47									.33	.43	.78	S11C474	.44	.60	1.17	S11E474
.56									.32	.41	.95	S11C564	.49	.65	1.17	S11E564
.68									.25	.42	1.17	S11C684	.47	.63	1.45	S11E684
.82									.28	.45	1.17	S11C824	.46	.63	1.70	S11E824
1.0									.32	.49	1.17	S11C105	.47	.64	1.95	S11E105
1.2									.36	.52	1.17	S11C125	.52	.69	1.95	S11E125
1.5									.41	.58	1.17	S11C155	.59	.76	1.95	S11E155
1.8									.46	.62	1.17	S11C185	.66	.82	1.95	S11E185
2.0									.49	.65	1.17	S11C205	.70	.87	1.95	S11E205
3.0									.47	.63	1.70	S11C305				
4.0									.50	.66	1.95	S11C405				
5.0									.57	.73	1.95	S11C505				
6.0									.63	.79	1.95	S11C605				
8.0									.74	.90	1.95	S11C805				
10.0									.84	1.00	1.95	S11C106				
12.0																
15.0																
18.0																
20.0																

**PRESENTLY
AVAILABLE IN
ROUND ONLY
("S21" SERIES)**

Add letter to the end of the part number to specify the tolerance.

± 20% = M ± 5% = J ± 2% = G
± 10% = K ± 3% = H ± 1% = F



Bishop Electronics Corporation

3729 San Gabriel River Parkway • Pico Rivera CA 90660
(562) 695-0446 (562) 692-9391 FAX: (562) 692-4008
email: sales@bishopelectronics.com

Revised
4-29-05